



## **16-Slot Chassis System for TFC series Fiber Converter**

### **TFC-1600**

TRENDnet's TFC-1600 16-slot EIA-19" Rack-Mount Chassis System provides housing for up to 16 TFC series media converters. Designed for continuous operation, the chassis is equipped with dual cooling fans and redundant power supplies (optional). Its Plug-and-Play and Hot-Swap features allow installing/removing the converter unit without powering off the chassis. TFC-1600 rack-mount chassis eliminates the external power adapters for TFC series media converters and organizes multiple converters in a single unit, which makes it the perfect solution for managing multiple TFC series converters.

### **FEATURES**

- Provides housing for up to 16 TFC series media converters
- Front panel LEDs indication tiation Mode for Fiber Port
- Standard 19" rack-mount size, 2U height
- Hot-Swappable; easy & quick replacement of converter and power supply
- Single cooling fan (internal) mounted at the rear panel
- Optional redundant power supply to ensure non-stop reliable operation
- Optional Management Module
- Load Sharing mechanism to minimize downtime (available only with redundant power supplies)
- Power isolation designed with converter bays: ensures each bay is electrically isolated from others
- 5 Year Warranty

### **BENEFITS**

- 1 x 10/100Mbps Fast Ethernet RJ45 port and 1 x RS-232 Console ports for management
- Web Browser Based Management via Ethernet port or Command Line Interface Management via RS-232 port
- SNMP Agent
- Provides media Link/Connection Speed/Duplex status for each module
- Provides Cooling Fans and Power Supplies status

# 16-Slot Chassis System for TFC series Fiber Converter

## TFC-1600

### SPECIFICATIONS

Hardware	
Capacity	• 16 slots for housing up to 16 TFC series media converters
Management Ports	• 1 x 10/100Mbps Fast Ethernet RJ45 and 1 x RS-232
Management Protocol	• SNMP(RFC1157), ARP(RFC826), IP(RFC791), ICMP(RFC792), UDP(RFC768), TCP(RFC793), TFTP(RFC783), Telnet(RFC854), BOOT(RFC951), MIB II (RFC1213)
Diagnostic LEDs	• Power x 2, In Use x 2, Fan Fault x 2
Power	• One power supply; optional second power supply
Input	• AC 100 ~ 240 VAC. Power Consumption: 150 watts max
Power Overload Protection	• All outputs protected from short circuit condition with automatic recovery
Cooling	• Single cooling fan (internal) mounted at the rear panel
Housing	• Steel sheet metal
Dimensions	• 415 x 390 x 89 mm (16.3 x 15.4 x 3.5 inches)
Weight	• appr. 7Kg (15.4 lbs) (with one power supply)
Temperature	• Operating: 0°~ 40°C (32°~ 104°F) • Storage: -10°~ 50°C (14°~ 122°F)
Humidity	• Operating: 10% ~ 90% • Storage: 5% ~ 90% (no-condensing)
Certifications	• FCC, CE, VCCI

### RELATED PRODUCTS

<b>TFC-1600</b>	16-Slot Chassis System for TFC series Fiber Converter
<b>TFC-1600RP</b>	Redundant Power Supply for the TFC-1600
<b>TFC-1600MM</b>	Management Module for the TFC-1600
<b>TFC-1600R48</b>	48V Redundant Power Supply for TFC-1600

### ORDERING INFORMATION

#### TRENDnet

3135 Kashiwa Street, Torrance, CA 90505 USA

Tel: 1-888-777-1550

Fax: 310-891-1111

Web: [www.trendnet.com](http://www.trendnet.com)

Email: [sales@trendnet.com](mailto:sales@trendnet.com)

To Order Please Call:

**1-888-326-6061**

